

GA 27 1/4-FME

Rubber Antenna with Universal FME-Connection System for Portable Equipment in the 27 MHz Band



DESCRIPTION:

- ★ Sturdy, conical, flexible rubber antenna.
- ★ Shortened 1/4 λ whip yields an acceptable mechanical length.
- ★ Highest quality materials – designed for “wear and tear”.
- ★ Delivered factory tuned and tested to ensure minimum SWR and optimum performance.
- ★ Provided with universal FME-connection system for optimum flexibility and easily exchangeable connectors.
- ★ Designed for use with the following of PROCOMs line of black FME-connectors (to be ordered separately): BFME-UHF, BFME-BNC, BFME-TNC, BFME-N and BFME-MQ.

SPECIFICATIONS:

ELECTRICAL	
ANTENNA TYPE	Shortened 1/4 λ antenna for portable equipment
FREQUENCY	27 MHz CB band
IMPEDANCE	Nom. 50 Ω
POLARISATION	Vertical
SWR	< 2 when mounted directly on portable equipment
MAX. POWER	25 watt
MECHANICAL	
MATERIALS	Steelwire moulded in thermoplastic rubber Black-chromed brass
COLOUR	Black
TOTAL HEIGHT	Approx. 500 mm
WEIGHT	Approx. 85 g
CONNECTOR	FME (female) (Exchangeable BFME-connectors to be ordered separately)

PLEASE NOTE:

The GA 27 1/4 is also available with different thread studs, but in this case with fixed, non-exchangeable connector (not FME-connection system). Information on these special versions on request.

RECOMMENDED BFME-CONNECTORS:

(To be ordered separately)

